



SOT-23 Plastic-Encapsulate Transistors

Features

• Cmplementary to MMBTA94

• 350 mW Power Dissipation of 350mW

• High Stability and High Reliability

Mechanical Data

• SOT-23 Small Outline Plastic Package

• Epoxy UL: 94V-0

• Mounting Position: Any





Marking: 3D

SOT-23

Pin definition



1. BASE

2. EMITTER 3. COLLECTOR

Maximum Ratings & Electrical Characteristics(TA=25°C unless otherwise noted)				
Parameter	Symbol	Value	Unit	
Collector-Base Voltage	V _{CBO}	400	V	
Collector-Emitter Voltage	V _{CEO}	400	V	
Emitter -Base Voltage	V _{EBO}	6	V	
Collector Current-Continuous	I _C	200	mA	
Collector Power Dissipation	Pc	350	mW	
Operating junction temperature range	TJ	150	°C	
Storage temperature range	T _{STG}	-55-+150	°C	
Thermal Resistance from Junction to Ambient	RөJA	357	°C/W	

Electrical Specifications(TA=25°C unless otherwise noted)						
Parameter	Symbol	Test Conditions	Limits		l lmi4	
		rest Conditions	Min	Max	Unit	
Collector-base breakdown voltage	$V_{(BR)CBO}$	IC=100uA, IE=0	400			
Collector-emitter breakdown voltage	V _{(BR)CEO}	IC=1mA, IB=0	400		V	
Emitter-base breakdown voltage	$V_{(BR)EBO}$	IE=10uA, IC=0	6			
Collector cut-off current	ICBO	VCB=400V, IE=0		100		
Emitter cut-off current	IEBO	VEB=4V, IC=0		100	nA	
DC current gain	hFE(1)*	VCE=10V, IC=1mA	40			
	hFE(2)*	VCE=10V, IC=10mA	50			
	hFE(3)*	VCE=10V, IC=50mA	45			
	hFE(4)*	VCE=10V, IC=100mA	40			
Collector-emitter saturation voltage	VCE(sat)1*	IC=1mA, IB=0.1mA		0.40		
Collector-emitter saturation voltage	VCE(sat)2*	IC=10mA, IB=1mA		0.50		
Collector-emitter saturation voltage	VCE(sat)3*	IC=50mA, IB=5mA		0.75	V	
Base -emitter saturation voltage	VBE(sat)*	IC=10mA, IB=1mA		0.75		
Collector output capacitance	Cob	VCB=20V, IE=0; f=1MHz		7	pF	
Emitter input capacitance	Cib	VeB=0.5V, IC=0; f=1MHz		130		


^{*}Pulse test: pulse width≤300us, duty cycle≤2. 0%





Ratings and Characteristics Curves


(TA = 25°C unless otherwise noted)







Package Outline Dimensions



SYMBOL	DIMENSIONS		
	MIN.	MAX.	
Α	0.900	1.150	
A1	0.000	0.100	
A2	0.900	1.050	
b	0.300	0.500	
С	0.080	0.150	
D	2.800	3.000	
E	1.200	1.400	
E1	2.250	2.550	
е	0.950TYP		
e1	1,800	2.000	
L	0.550REF		
L1	0.300	0.500	
θ	0°	8°	

Revision History

Document Version	Date of release	Description of changes
Rev.A	2017.06.13	First issue





Disclaimers

These materials are intended as a reference to assist our customers in the selection of the Suzhou Good-Ark product best suited to the customer's application; they do not convey any license under any intellectual property rights, or any other rights, belonging to Suzhou Good-Ark Electronics Co., Ltd.or a third party.

Suzhou Good-Ark Electronics Co., Ltd. assumes no responsibility for any damage, or infringement of any third-party's rights, originating in the use of any product data, diagrams, charts, programs, algorithms, or circuit application examples contained in these materials.

All information contained in these materials, including product data, diagrams, charts, programs and algorithms represents information on products at the time of publication of these materials, and are subject to change by Suzhou Good-Ark Electronics Co., Ltd. without notice due to product improvements or other reasons. It is therefore recommended that customers contact Suzhou Good-Ark Electronics Co., Ltd. or an authorized Suzhou Good-Ark Electronics Co., Ltd. for the latest product information before purchasing a product listed herein. The information described here may contain technical inaccuracies or typographical errors. Suzhou Good-Ark Electronics Co., Ltd. assumes no responsibility for any damage, liability, or other loss rising from these inaccuracies or errors. Please also pay attention to information published by Suzhou Good-Ark Electronics Co., Ltd. by various means, including our website home page. (http://www.goodark.com)

When using any or all of the information contained in these materials, including product data, diagrams, charts, programs, and algorithms, Please be sure to evaluate all information as a total system before making a final decision on the applicability of the information and products. Suzhou Good-Ark Electronics Co., Ltd. assumes no responsibility for any damage, liability or other loss resulting from the information contained herein.

The prior written approval of Suzhou Good-Ark Electronics Co., Ltd. is necessary to reprint or reproduce in whole or in part these materials.

Please contact Suzhou Good-Ark Electronics Co., Ltd. or an authorized distributor for further details on these materials or the products contained herein.