

8A,1200V Ultrafast Recovery Rectifier

Features

- FRED Wafer Construction
- Low forward drop voltage, low power loss
- High Surge Current Capability
- Plastic package has underwriters Laboratory Flammability Classification 94V-0
- Halogen-free according to IEC 61249-2-21



TO-263AB(D²PAK)




- SMPS
- Adapter
- Server Power

Mechanical Data

- Case: Epoxy, Molded
- Finish: All External Surfaces Corrosion Resistant and Terminal Leads are Readily Solderable
- Lead Temperature for Soldering Purposes: 260°C Max. for 10 sec
- Shipped 50 units per plastic tube or tape reel packing 800/reel

Maximum Ratings & Electrical Characteristics(TA=25°C unless otherwise noted)				
Parameter	Symbol	MURB8120S	Unit	
Maximum repetitive peak reverse voltage	Vrrm	1200	V	
Working peak reverse voltage	VRWM	1200	V	
Maximum DC blocking voltage	VDC	1200	V	
Maximum average forward rectified current	lf(AV)	8	А	
Peak forward surge current,8.3ms single half sine-wave superimposed on rated load	IFSM	80	А	
Voltage rate of change (rated VR)	dv/dt	10000	V/uS	
Operating junction temperature range	TJ	-55 to +150	°C	
Storage temperature range	Тѕтс	-55 to +150	°C	



Electrical Specifications(TA=25°C unless otherwise noted)						
Parameter	Symbol	Test Conditions	Тур	Max	Unit	
Forward drap voltage (Note1)	VF	IF=8A, TJ =25℃	2.00	2.60		
Forward drop voltage (Note1)		IF=8A, TJ =125℃ -		2.20	V	
	IR	TJ =25 ℃	-	10		
Reverse leakage current @VR ^(Note2)		TJ =100℃	-	500	uA	
Reverse recovery time	trr	IF=0.5A, IR=1.0A, IRR=0.25A	-	50	ns	

Thermal-Mechanical Specifications (TA=25°C unless otherwise noted)					
Parameter	Symbol	Тур	Unit		
Thermal Resistance, Junction to Case	Rejc	2.0	°C /W		
Thermal Resistance, Junction to Ambient	Reja	62.5	°C /W		


Note:

- 1. Pulse test with PW=0.3ms, duty cycle=2%
- 2. Pulse test with PW=30ms



MURB8120S GOOD-ARK Electronics

Ratings and Characteristics Curves






Fig.3 – Typical Forward Voltage Characteristics





Fig.5 – Typical Junction Capacitance










Fig.4 – Typical Reverse Current Characteristics





Package Outline Dimensions (Unit: millimeters)


TO-263AB












TO-263AB							
	Min.	Nom.	Max.		Min.	Nom.	Max.
А	9.8	10	10.2	C3	5	5.3	5.6
A1	6.5			Е	1.17	1.37	1.57
A2	4.4	4.6	4.8	E1	2.44	2.54	2.64
A3	1.17	1.27	1.37	E2	1.17	1.27	1.37
A4	2.37	2.67	2.97	E3	0.7	0.8	0.9
В	8.5	8.7	8.9	E4	6.47	6.67	6.87
B1	1.07	1.27	1.47	E5	8.3	8.5	8.7
B2	1.2	1.5	1.8	Z		3°	
B3	15	15.3	15.6	Z1		3°	
B4	1.8	2	2.2	Z2		30°	
С	0		0.25	Z3		7°	
C1	2.34	2.54	2.74	Z4		7°	
C2	0.3	0.4	0.5	Z5	-4°		4°



Marking Outline



Revision History

Document Version	Date of release	Description of changes
Rev.A	2022.12.30	Preliminary Datasheet



Disclaimers

These materials are intended as a reference to assist our customers in the selection of the Suzhou Good-Ark product best suited to the customer's application; they do not convey any license under any intellectual property rights, or any other rights, belonging to Suzhou Good-Ark Electronics Co., Ltd.or a third party.

Suzhou Good-Ark Electronics Co., Ltd. assumes no responsibility for any damage, or infringement of any thirdparty's rights, originating in the use of any product data, diagrams, charts, programs, algorithms, or circuit application examples contained in these materials.

All information contained in these materials, including product data, diagrams, charts, programs and algorithms represents information on products at the time of publication of these materials, and are subject to change by Suzhou Good-Ark Electronics Co., Ltd. without notice due to product improvements or other reasons. It is therefore recommended that customers contact Suzhou Good-Ark Electronics Co., Ltd. or an authorized Suzhou Good-Ark Electronics Co., Ltd. for the latest product information before purchasing a product listed herein. The information described here may contain technical inaccuracies or typographical errors. Suzhou Good-Ark Electronics Co., Ltd. assumes no responsibility for any damage, liability, or other loss rising from these inaccuracies or errors. Please also pay attention to information published by Suzhou Good-Ark Electronics Co., Ltd. by various means, including our website home page. (http://www.goodark.com)

When using any or all of the information contained in these materials, including product data, diagrams, charts, programs, and algorithms, Please be sure to evaluate all information as a total system before making a final decision on the applicability of the information and products. Suzhou Good-Ark Electronics Co., Ltd. assumes no responsibility for any damage, liability or other loss resulting from the information contained herein.

The prior written approval of Suzhou Good-Ark Electronics Co., Ltd. is necessary to reprint or reproduce in whole or in part these materials.

Please contact Suzhou Good-Ark Electronics Co., Ltd. or an authorized distributor for further details on these materials or the products contained herein.